


Yealink Overrides

Scope

 The below codes will allow you to set overrides in the program of Yealink phones.

Items Needed

- Text editor
- Access to NDP server or Advanced tab in Manager Portal

Yealink Administrator Guide

<http://support.yealink.com/documentFront/forwardToDocumentDetailPage?documentId=143>

Null Values

You can override any provisioned value by entering %NULL%
I.e. `firmware.url.server_type="%NULL%"`

Directed Call Pickup

```
features.pickup.direct_pickup_enable="1"  
features.pickup.direct_pickup_code="*35"
```

Distinctive Ring

The Distinctive Ring feature works by adding a department name to the extension

```
account.1.alert_info_url_enable="1"  
distinctive_ring_tones.alert_info.1.text="Restaurant"  
distinctive_ring_tones.alert_info.1.ringer="2"
```

The example above will cause any Yealink phone to use Ringer 2 whenever a call is received from a member of the 'Restaurant' department.

Wallpaper Sizes

Phone Model	Image Format	Resolution	Single File Size	Total File Size
VP530	.jpg, .png, .bmp	1920*1200		
SIP-T29G	.jpg, .jpeg, .png, .bmp	480*272, 1.8MP	<= 5MB	
SIP-T32G	.jpg, .png, .bmp	480*272		
SIP-T38G	.jpg, .png, .bmp	480*272		
SIP-T46G	.jpg, .jpeg, .png, .bmp	480*272, 1.8MP	<= 5MB	
SIP-T46S	.jpg, .jpeg, .png, .bmp	480*272, 1.8MP		
SIP-T48G	.jpg, .jpeg, .png, .bmp	800*480, 2MP	<= 5MB	
SIP-T48S	.jpg, .jpeg, .png, .bmp	800*480, 2MP	<= 5MB	<= 20MB
SIP-T52S	.jpg, .jpeg, .png, .bmp	320*240, 4.2MP	<= 5MB	
SIP-T54S	.jpg, .jpeg, .png, .bmp	480*272, 4.2MP	<= 5MB	
SIP-T54W	.jpg, .jpeg, .png, .bmp	480*272, 2MP	<= 5MB	
EXP50	.jpg, .jpeg, .png, .bmp	272*480, 4.2MP	<= 5MB	

Original Yealink FAQ <http://support.yealink.com/faq/faqInfo?id=219>

Default Wallpaper

phone_setting.backgrounds="Config:Default.jpg"

Wallpaper T46G

phone_setting.backgrounds="Config:t46g.jpg"
wallpaper_upload.url="<http://oitvoip.com/images/t46g.jpg>"

Wallpaper T48G

phone_setting.backgrounds="Config:t48g.png"
wallpaper_upload.url="<http://oitvoip.com/images/t48g.jpg>"

Allow Remote Control From IPs

features.action_uri_limit_ip="any"
or
features.action_uri_limit_ip="192.168.0.1"

Programmable Key

(Replace 'X' with the number of the key you are setting)

programmablekey.X.type=
programmablekey.X.line=
programmablekey.X.value=
programmablekey.X.xml_phonebook=
programmablekey.X.history_type=
programmablekey.X.label=

Line Key Types

0-NA
1-Conference
2-Forward
3-Transfer
4-Hold
5-DND
7-Call Return
8-SMS
9-Directed Pickup
10-Call Park
11-DTMF
12-Voice Mail
13-Speed Dial
14-Intercom
15-Line
16-BLF
17-URL
18-Group Listening
20-Private Hold
22-XML Group
23-Group Pickup
24-Multicast Paging
25-Record
27-XML Browser
34-Hot Desking
35-URL Record
38-LDAP
39-BLF List
40-Prefix
41-Zero Touch
42-ACD
45-Local Group
46-Network Group
49-Custom Button
50-Keypad Lock
55-Meet-Me Conference
56-Retrieve Park
57-Hoteling
58-ACD Grace
59-Sisp Code

60-Emergency
61-Directory

0-NA Only for T41/T42/T46)
22-XML Group (Not support T20)
38-LDAP (Not support T20)
46-Network Group (Not support T20)
8-SMS (Only support T21/T46/T22/T26/T28)
17-URL (Only support T41/T42/T46)
49-Custom Button (Only support T20/T22/T26/T28)

DND Sync

bw.feature_key_sync="0"

Daylight Savings Time

0 = Disabled 1 = Enabled 2= Automatic

local_time.summer_time="0"

Time Format

0 = 12- Hour Format 1 = 24- Hour Format

local_time.time_format = "0"

Jitter Buffer to Fixed

voice.jib.adaptive="1"
voice.jib.min="120"
voice.jib.max="120"
voice.jib.normal="120"

SIP Scanner Protection

features.direct_ip_call_enable="0"
sip.trust_ctrl="1"
sip_trust_ctrl="1" (only for Firmware under v80)

Provisioning Guide



Yealink_SIP-T2_S...Guide_V73_40.pdf